

## LIGHTING CONTROLS

### DIMMABLE ELECTRONIC TRANSFORMERS FOR 12V DOWNLIGHTS

#### 12V IP65 Dimmable Electronic Transformers

- 12V power supply for MR16 lamps
- Pre-heat soft-start function for input voltage surge protection. Suitable for 2-way switching with standard switch.
- Integral in-line fuse to ensure complete safety at end of life
- Thermal fuse – ensures safe failure if in excess of ambient temperature
- Radio interference suppression in accordance with EN55015
- Safety & performance in accordance with EN61347-22
- RAPS-70/105D comes with 400m mains voltage primary leads & 400m 12V secondary leads and is IP65, suitable for outdoor use when mounted vertically with cables facing down
- RM70DN/RM105DN have large mains terminals for loop in and loop out suitable 2 x 1.5 T&E cables. In case of short circuit the RM70DN/RM105DN will automatically reset when fault is removed
- RM70DN/RM105DN are IP20

	Cylinder	Rectangular
	<b>RAPS-70D</b>	<b>RM70DN</b>
	<b>RAPS-105D</b>	<b>RM105DN</b>
<b>Total Power (W):</b>	70/105	70/105
<b>Diameter (mm):</b>	35	45
<b>Length (mm):</b>	140	120
<b>Box Qty:</b>	<b>10</b>	<b>30</b>
<b>Weight (kg):</b>	0.2	0.13
<b>IP:</b>	65	20



RAPS



RM70DN

