









180mA CONSTANT CURRENT CONVERTERS

technical info

BEAUFORT	TYPE
MINI TOMMY, MINI ECLIPS, INCAS R, QUAD, HELVA, INTANA	FIXTURE
180	MAX. CURRENT
6,22	P (W)
34,6	TYPICAL FORWARD VOLTAGE V_f

Artnr	Converter Type	Strain Relief	Application	Dimmable	IP	Class	Input voltage (V)	Output range (V)	Luminaire Quantity
930547	POWERLED CONVERTOR 7,2W SMALL	YES	INDOOR	NOT	20	□	110-240	20-43	1
930544	POWERLED CONVERTOR 7,2W MAINS DIMM C (*)	YES	INDOOR	MAINS DIMM C	20	□	230-240	20-40	1
930565	POWERLED CONVERTOR 10W MAINS DIMM L,C (10%)	YES	INDOOR	MAINS DIMM L,C	20	□	220-240	28-56	1
930565	POWERLED CONVERTOR 10W DIMMABLE 1-10V	YES	INDOOR	1-10V	20	□	220-240	28-56	1
930588	POWERLED CONVERTOR 15W DALI/TOUCH DIMM	YES	INDOOR	DALI / TOUCH DIMM	20	□	198-264	20-54	1
930545	POWERLED CONVERTOR 2.5-15W	YES	INDOOR	NOT	20	□	90-264	0-41,5	1
930546	POWERLED CONVERTOR 1-20W DIMMABLE 1-10V	YES	INDOOR	1-10V	20	□	110-240	3-43	1
930549	POWERLED CONVERTOR 2X 8W DIMMABLE 1-10V	YES	INDOOR	1-10V	20	□	110-240	3-45	1-2

(*) 10% - 30%: SEE LIST COMPATIBLE DIMMERS

NOT DIMMABLE	MAINS DIMM C	MAINS DIMm L/C + 1-10V DIMM	1-10V DIMM	DALI/TOUCH DIMM
 <p>930545 POWERLED CONVERTOR REMOTE 2.5-15W 180mA</p>	 <p>930544 POWERLED CONVERTOR REMOTE 7,2W 180mA MAINS DIMM C</p>	 <p>930565 POWERLED CONVERTOR REMOTE 10W 180mA MAINS DIMM L,C (10%)</p>	 <p>930546 POWERLED CONVERTOR REMOTE 1-20W 180mA DIMMABLE 1-10V</p>	 <p>930588 POWERLED CONVERTOR 15W 180mA DALI/TOUCH DIMM</p>
 <p>930547 POWERLED CONVERTOR REMOTE 7,2W 180mA SMALL</p>			 <p>930549 POWERLED CONVERTOR 2X 180mA 1-10V DIMM</p>	
			 <p>930565 POWERLED CONVERTOR REMOTE 10W 180mA 1-10V DIMM</p>	