

BEGA**13 566**

Smart Tower

IP 65

Project · Reference number

Date

Product data sheet

Application

Smart Tower with connecting cable and mains plug for the BEGA Plug & Play LED light system. Each of the 4 outputs can be switched and dimmed individually.

Configuration is carried out via the convenient BEGA Smart app (for iOS and Android). To operate the LED light system, we recommend the remote controls PRO (13 569) or ONE (10 526).

Product description

Housing and earth spike made of glass fibre reinforced synthetic material (polyamide)

DC safety power supply

Primary: 220-240 V ~ 50-60 Hz

5 m mains supply cable H05RN-F 3 × 1[□] with mains plug

Secondary: 48V = DC · 0-50 W

Zigbee 3.0 and Bluetooth 4.2

4 outputs can be switched and dimmed individually for connection of luminaires and Smart Extender

Connected wattage max. 50 W

Ambient temperature: -20°C bis +50°C

Protection class IP 65

Dust-tight and protection against water jets

CE – Conformity mark

Weight: 1.0 kg

Range

The Zigbee radio range between the individual devices is max. 30 m, but the ambient conditions play a decisive role. In difficult conditions, we recommend the additional use of the 71 055 router module.

Accessories

10 526 Remote control ONE

13 569 Remote control PRO

13 568 Smart Extender

Distributor with 5 m cable and 48 V plug, switchable and dimmable via Zigbee Control module

10 596 Extension cable 5 m

10 597 Extension cable 10 m

70 588 Gateway

for controlling your lighting system by app BEGA Gateway from a smartphone or tablet

