

BEGA**55 008**

Plug & Play Garden luminaire

IP 65

Project · Reference number

Date

Product data sheet

Application

BEGA Plug & Play

Portable garden luminaire with earthspike, connecting cable and 48 V plug.

Luminaire with opal glass for a soft and uniform light distribution.

Product description

Luminaire with earthspike made of glass-fibre reinforced polyamide synthetic

Opal glass with screw neck

Silicone gasket

5 m mains supply cable with 48 V plug

Safety class III ⚡

Protection class IP 65

Dust-tight and protection against water jets

Impact strength IK06

Protection against mechanical

impacts < 1 joule

CE – Conformity mark

Weight: 1.0 kg

Lighting technologyLuminaire data for the DIALux lighting design program for outdoor lighting, street lighting and indoor lighting, as well as luminaire data in EULUMDAT and IES format are available on the BEGA website at www.bega.com.**Lamp**

Module connected wattage 1.9 W

Luminaire connected wattage 2.4 W

Rated temperature $t_a = 25 \text{ °C}$ Ambient temperature $t_{a \text{ max}} = 60 \text{ °C}$

Voltage 48 V = DC

55 008 K3

Module designation LED-0684/830


Colour temperature 3000 K

Colour rendering index CRI > 80

Module luminous flux 290 lm

Luminaire luminous flux 186 lm

Luminaire luminous efficiency 77,5 lm/W

**Service life · Ambient temperature**Rated temperature $t_a = 25 \text{ °C}$

LED psu: > 50,000h

LED module: > 200,000h (L80B50)
100,000h (L90B50)Ambient temperature max. $t_a = 60 \text{ °C}$ (100 %)

LED psu: 50,000h

LED module: 160,000h (L80B50)

Accessories**13 566** Smart Tower with connecting cable and mains plug**13 567** Smart Tower with connecting cable and free cable end**13 568** Smart Extender Distributor with 5 m cable and 48V plug, switchable and dimmable via Zigbee Control module**10 596** Extension cable 5 m**10 597** Extension cable 10 m**10 526** Remote control ONE**13 569** Remote control PRO**70 588** Gateway for controlling your lighting system by app BEGA Gateway from a smartphone or tablet

For the accessories a separate instructions for use can be provided upon request.

Light distribution