



## ENTERO SQ-M X 92710 B

28542 9210 B



AVAILABLE IN

**BLACK** 28542 9210 B

**FLEMISH BRONZE OUTDOOR** 28542 9210 FBRX

**ANTHRACITE (DARK GREY)** 28542 9210 N

**WHITE** 28542 9210 W



 [View on website](#)

### General info

<b>LOCATION</b>	outdoor
<b>INSTALLATION</b>	Ceiling Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	square - 92 x 92
<b>RECESSED DEPTH (MM)</b>	140
<b>THICKNESS OF MOUNTING SURFACE (MM)</b>	12,5 or 25
<b>INGRESS PROTECTION</b>	IP65
<b>PROTECTION AGAINST MECHANICAL IMPACT</b>	IK06
<b>WEIGHT (KG)</b>	0.495
<b>ADJUSTABILITY</b>	0° to 20° swiveling, 355° rotatable
<b>INFORMATION</b>	LENS SP-10° EXCL.LED POWER SUPPLY 350-700mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on type of external power supply
<b>ENERGY CLASS</b>	F
<b>CERTIFICATES</b>	CB, ENEC

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 3,9-8,2W / CRI>90 (R9: 56) / 2700K / 385-677lm
<b>TM-30 VALUES</b>	Rf: 91 / Rg: 99
<b>SDCM</b>	SDCM2
<b>RISKGROUP</b>	RG2 (threshold 0,6m)
<b>LM80</b>	L90B10 > 41000
<b>LED TECHNICS (LIGHT SOURCE)</b>	677lm // 8,2W // 83lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	555lm // 9W // 59lm/W

### Requirements

LED POWER SUPPLY 350 / 500 / 700mA-DC DIM

### Accessories

ENTERO M HONEYCOMB

# ENTERO SQ-M X 92710 B

28542 9210 B

For detailed installation instructions, please consult the manual: [28542\\_XXX0\\_HAND.pdf](#)

## CEILING COMPATIBILITY

Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-
 Stretched ceiling	-




**ENTERO SQ-M X 92710 B**

28542 9210 B


**LED power supplies**

#




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9

1->6(6) / 1->5(5) / 1->5(4)




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5

1->4(3) / 1->4(2) / 1->3(2) / 1->3(1)




**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9

3->9(9) / 1->9(6) / 1->6(4)




**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7

2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)




**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5

2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)




**21012 0010** LED POWER SUPPLY MULTI POWER

2->3 / 2->3 / 1->3




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1

2->4 / 2->4 / 1->4



**21012 0035** LED POWER SUPPLY MULTI POWER DIM5

2->4 / 2->4 / 1->4




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL

1->4 / 1->4 / 1->4 / 1->4


# ENTERO SQ-M X 92710 B

28542 9210 B




**21012 0258** LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

2->2




**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

3->3




**21012 0278** LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

2->2 / 2->2




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

4->4 / 3->4




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->3 / 1->3 / 1->3 / 1->2




**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->3



**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5


1->3



**21032 0315** LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5

1->3

## Light altering devices



**28500 0110 B** ENTERO M HONEYCOMB SINGLE USE B



## **ENTERO SQ-M X 92710 B**

28542 9210 B

Notes: