



## BOXY XL R 92720 DIM1 W-W



251 71 21 921 ED1 W-W

AVAILABLE IN

**BLACK-BLACK** 251 71 21 921 ED1 B-B

**WHITE-BLACK** 251 71 21 921 ED1 W-B

**WHITE-WHITE** 251 71 21 921 ED1 W-W



 [View on website](#)

### General info

<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Ceiling Surface mounted
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	1.5
<b>ADJUSTABILITY</b>	non adjustable
<b>INFORMATION</b>	REFLECTOR FL-20° INCL.DIMMABLE LED POWER SUPPLY 700mA-DC

### Electrical info

<b>ELECTRICAL</b>	120-240V / 50-60Hz
<b>CLASS</b>	II
<b>POWER SUPPLY INCLUDED</b>	YES
<b>DIM TYPE</b>	1-10V
<b>ENERGY CLASS</b>	D
<b>CERTIFICATES</b>	CB, ENEC

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 23,2W / CRI>90 (R9: 60) / 2700K / 3031lm
<b>TM-30 VALUES</b>	Rf: 89 / Rg: 100
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	3031lm // 23,2W // 130lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	2636lm // 27W // 99lm/W

### Accessories

HONEYCOMB 78  
SOFTENING LENS 78  
GLASS SBL 78

# BOXY XL R 92720 DIM1 W-W


251 71 21 921 ED1 W-W

For detailed installation instructions, please consult the manual: [251\\_71\\_21\\_XXX\\_ED1\\_HAND.pdf](#)

## FINISH YOUR SPECIFICATION

### Control gear, ballast and transformers


---



**300 90 016 ED1** WIRELESS CONTROL 5A DIM1

### Light altering devices

---



Ø78

**201 02 01 B** HONEYCOMB 78 B



Ø78

**201 02 04** SOFTENING LENS 78



Ø78

**201 02 05** GLASS SBL 78

Notes: