



ENTERO RD-M X 92710 W

28442 9210 W



AVAILABLE IN

BLACK 28442 9210 B

FLEMISH BRONZE OUTDOOR 28442 9210 FBRX

ANTHRACITE (DARK GREY) 28442 9210 N

WHITE 28442 9210 W



[View on website](#)

General info

LOCATION	outdoor
INSTALLATION	Ceiling Recessed
CUTOUT SHAPE/SIZE (MM)	round - 92
RECESSED DEPTH (MM)	140
THICKNESS OF MOUNTING SURFACE (MM)	max.16
INGRESS PROTECTION	IP65
PROTECTION AGAINST MECHANICAL IMPACT	IK06
WEIGHT (KG)	0.49
ADJUSTABILITY	0° to 20° swiveling, 355° rotatable
INFORMATION	LENS SP-10° EXCL.LED POWER SUPPLY 350-700mA-DC

Electrical info

CLASS	III
DIM TYPE	depending on type of external power supply
ENERGY CLASS	F
CERTIFICATES	CB, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 3,9-8,2W / CRI>90 (R9: 56) / 2700K / 385-677lm
TM-30 VALUES	Rf: 91 / Rg: 99
SDCM	SDCM2
RISKGROUPE	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED TECHNICS (LIGHT SOURCE)	677lm // 8,2W // 83lm/W
LED TECHNICS (LUMINAIRE)	553lm // 9W // 59lm/W

Requirements

LED POWER SUPPLY 350 / 500 / 700mA-DC DIM

Options

ENTERO RD-M MOUNTING SET S2

ENTERO RD-M X 92710 W














28442 9210 W

Accessories

ENTERO M HONEYCOMB

For detailed installation instructions, please consult the manual: [28442_XXX0_HAND.pdf](#)

CEILING COMPATIBILITY


Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-
 Concrete	 ENTERO RD-M MOUNTING SET S2 Required
 Concrete + plaster	 ENTERO RD-M MOUNTING SET S2 Required
 Lintel + plaster	 ENTERO RD-M MOUNTING SET S2 Required
 Hollow-core slab	 ENTERO RD-M MOUNTING SET S2 Required
 Hollow-core slab + plaster	 ENTERO RD-M MOUNTING SET S2 Required
 Stretched ceiling	-

ENTERO RD-M X 92710 W

28442 9210 W


LED power supplies

#




300 90 63 LED POWER SUPPLY MULTI-POWER DIM9

1->6(6) / 1->5(5) / 1->5(4)




300 90 68 LED POWER SUPPLY MULTI-POWER DIM5

1->4(3) / 1->4(2) / 1->3(2) / 1->3(1)




300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9

3->9(9) / 1->9(6) / 1->6(4)




300 90 124 LED POWER SUPPLY MULTI-POWER DIM7

2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)




300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5

2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)




21012 0010 LED POWER SUPPLY MULTI POWER

2->3 / 2->3 / 1->3




21012 0021 LED POWER SUPPLY MULTI POWER DIM1

2->4 / 2->4 / 1->4



21012 0035 LED POWER SUPPLY MULTI POWER DIM5

2->4 / 2->4 / 1->4




21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL

1->4 / 1->4 / 1->4 / 1->4


ENTERO RD-M X 92710 W

28442 9210 W




21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

2->2




21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

3->3




21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

2->2 / 2->2




21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

4->4 / 3->4




21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->3 / 1->3 / 1->3 / 1->2




21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->3



21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5


1->3



21032 0315 LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5

1->3

Light altering devices




28500 0110 B ENTERO M HONEYCOMB SINGLE USE B

ENTERO RD-M X 92710 W

28442 9210 W

Mounting set S2



28500 0200 ENTERO RD-M MOUNTING SET S2



Notes: