



ENTERO SQ-M X 93010 B

28542 9310 B



AVAILABLE IN

BLACK 28542 9310 B

FLEMISH BRONZE OUTDOOR 28542 9310 FBRX

ANTHRACITE (DARK GREY) 28542 9310 N

WHITE 28542 9310 W



[View on website](#)

General info

LOCATION	outdoor
INSTALLATION	Ceiling Recessed
CUTOUT SHAPE/SIZE (MM)	square - 92 x 92
RECESSED DEPTH (MM)	140
THICKNESS OF MOUNTING SURFACE (MM)	12,5 or 25
INGRESS PROTECTION	IP65
PROTECTION AGAINST MECHANICAL IMPACT	IK06
WEIGHT (KG)	0.495
ADJUSTABILITY	0° to 20° swiveling, 355° rotatable
INFORMATION	LENS SP-10° EXCL.LED POWER SUPPLY 350-700mA-DC

Electrical info

CLASS	III
DIM TYPE	depending on type of external power supply
ENERGY CLASS	F
CERTIFICATES	CB, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 3,9-8,2W / CRI>90 (R9: 55) / 3000K / 385-677lm
TM-30 VALUES	Rf: 92 / Rg: 98
SDCM	SDCM2
RISKGROUPE	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED TECHNICS (LIGHT SOURCE)	677lm // 8,2W // 83lm/W
LED TECHNICS (LUMINAIRE)	555lm // 9W // 59lm/W

Requirements

LED POWER SUPPLY 350 / 500 / 700mA-DC DIM

Accessories

ENTERO M HONEYCOMB

ENTERO SQ-M X 93010 B

28542 9310 B

For detailed installation instructions, please consult the manual: [28542_XXX0_HAND.pdf](#)

CEILING COMPATIBILITY


Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-
 Stretched ceiling	-

ENTERO SQ-M X 93010 B

28542 9310 B

FINISH YOUR SPECIFICATION

Emergency units



21032 0270 B EMERGENCY UNIT 7W /1h + LED INDICATOR HOLDER B


21032 0270 W EMERGENCY UNIT 7W /1h + LED INDICATOR HOLDER W

ENTERO SQ-M X 93010 B

28542 9310 B


LED power supplies

#




300 90 63 LED POWER SUPPLY MULTI-POWER DIM9

1->6(6) / 1->5(5) / 1->5(4)




300 90 68 LED POWER SUPPLY MULTI-POWER DIM5

1->4(3) / 1->4(2) / 1->3(2) / 1->3(1)




300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9

3->9(9) / 1->9(6) / 1->6(4)




300 90 124 LED POWER SUPPLY MULTI-POWER DIM7

2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)




300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5

2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)




21012 0010 LED POWER SUPPLY MULTI POWER

2->3 / 2->3 / 1->3




21012 0021 LED POWER SUPPLY MULTI POWER DIM1

2->4 / 2->4 / 1->4



21012 0035 LED POWER SUPPLY MULTI POWER DIM5

2->4 / 2->4 / 1->4




21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL

1->4 / 1->4 / 1->4 / 1->4


ENTERO SQ-M X 93010 B

28542 9310 B




21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

2->2




21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

3->3




21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

2->2 / 2->2




21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

4->4 / 3->4




21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->3 / 1->3 / 1->3 / 1->2




21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->3



21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5


1->3



21032 0315 LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5

1->3

Light altering devices



28500 0110 B ENTERO M HONEYCOMB SINGLE USE B



ENTERO SQ-M X 93010 B

28542 9310 B

Notes: