



## ENTERO SQ-M X 93030 B

28543 9320 B



AVAILABLE IN

**BLACK** 28543 9320 B

**FLEMISH BRONZE OUTDOOR** 28543 9320 FBRX

**ANTHRACITE (DARK GREY)** 28543 9320 N

**WHITE** 28543 9320 W



[View on website](#)

### General info

<b>LOCATION</b>	outdoor
<b>INSTALLATION</b>	Ceiling Recessed
<b>CUTOUT SHAPE/SIZE (MM)</b>	square - 92 x 92
<b>RECESSED DEPTH (MM)</b>	140
<b>THICKNESS OF MOUNTING SURFACE (MM)</b>	12,5 or 25
<b>INGRESS PROTECTION</b>	IP65
<b>PROTECTION AGAINST MECHANICAL IMPACT</b>	IK06
<b>WEIGHT (KG)</b>	0.465
<b>ADJUSTABILITY</b>	0° to 20° swiveling, 355° rotatable
<b>INFORMATION</b>	REFLECTOR FL-30° EXCL.LED POWER SUPPLY 350-500mA-DC

### Electrical info

<b>CLASS</b>	III
<b>DIM TYPE</b>	depending on type of external power supply
<b>ENERGY CLASS</b>	E
<b>CERTIFICATES</b>	CB, ENEC

### Lightsource info

<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 11,6-17,2W / CRI>90 (R9: 52) / 3000K / 1524-2101lm
<b>TM-30 VALUES</b>	Rf: 90 / Rg: 99
<b>SDCM</b>	SDCM1
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	2101lm // 17,2W // 123lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	1291lm // 20W // 65lm/W

### Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

## ENTERO SQ-M X 93030 B

28543 9320 B




### Accessories

---

- ENTERO M HONEYCOMB
- ENTERO M LINEAR SPREAD LENS
- ENTERO M SPREAD LENS
- ENTERO M SOFTENING LENS
- ENTERO M GLASS SBL

For detailed installation instructions, please consult the manual: [28543\\_XXXO\\_HAND.pdf](#)

## CEILING COMPATIBILITY

Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-
 Stretched ceiling	-


## ENTERO SQ-M X 93030 B

28543 9320 B

### FINISH YOUR SPECIFICATION

#### Emergency units

---



**21032 0270 B** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER B

---


**21032 0270 W** EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER W

# ENTERO SQ-M X 93030 B

28543 9320 B


## LED power supplies

#




**300 90 63** LED POWER SUPPLY MULTI-POWER DIM9

1->2(2) / 1->2(2)




**300 90 68** LED POWER SUPPLY MULTI-POWER DIM5

1(1) / 1(0)



**300 90 69** LED POWER SUPPLY MULTI-POWER HV DIM9

1->3(3) / 1->3(2)




**300 90 124** LED POWER SUPPLY MULTI-POWER DIM7

1(1) / 1(0)




**300 90 125** LED POWER SUPPLY MULTI-POWER MINI DIM5

1(1) / 1(0)




**21012 0010** LED POWER SUPPLY MULTI POWER

1/1




**21012 0021** LED POWER SUPPLY MULTI POWER DIM1

1/1



**21012 0035** LED POWER SUPPLY MULTI POWER DIM5

1/1




**21012 005W** LED POWER SUPPLY MULTI-POWER COMPACT WDL

1/1


# ENTERO SQ-M X 93030 B

28543 9320 B




**21012 0268** LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

1




**21012 0288** LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

1




**21012 0298** LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1/1



**21032 0295** LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1



**21032 0305** LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5


1

# ENTERO SQ-M X 93030 B


28543 9320 B

## Light altering devices


---




**28500 0070** ENTERO M LINEAR SPREAD LENS




**28500 0080** ENTERO M SPREAD LENS



**28500 0090** ENTERO M SOFTENING LENS



**28500 0100** ENTERO M GLASS SBL



**28500 0110 B** ENTERO M HONEYCOMB SINGLE USE B

Notes: