



ENTERO RD-L TRIMLESS 93010 W



28434 9310 W

AVAILABLE IN

BLACK 28434 9310 B

GOLD COLOURED 28434 9310 GC

WHITE 28434 9310 W



 [View on website](#)



General info

LOCATION	indoor
INSTALLATION	Ceiling Recessed
CUTOUT SHAPE/SIZE (MM)	round - Ø KIT
RECESSED DEPTH (MM)	165
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.735
ADJUSTABILITY	0° to 30° swiveling, 355° rotatable
INFORMATION	LENS SP-10° EXCL.LED POWER SUPPLY 350-900mA-DC

Electrical info

CLASS	III
DIM TYPE	depending on type of external power supply
ENERGY CLASS	G
CERTIFICATES	CB, ENEC

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 3,9-10,7W / CRI>90 (R9: 55) / 3000K / 385-814lm
TM-30 VALUES	Rf: 92 / Rg: 98
SDCM	SDCM2
RISKGROUP	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED TECHNICS (LIGHT SOURCE)	814lm // 10,7W // 76lm/W
LED TECHNICS (LUMINAIRE)	708lm // 12W // 58lm/W

Requirements

MOUNTING KIT ENTERO ROUND L
LED POWER SUPPLY 350 / 500 / 700 / 900mA-DC DIM

Accessories


















ENTERO L HONEYCOMB

ENTERO RD-L TRIMLESS 93010 W

28434 9310 W

For detailed installation instructions, please consult the manual: [28434_XXX0_HAND.pdf](#)

CEILING COMPATIBILITY

Ceiling Type	Mounting Kit	
 System ceiling	 MOUNTING KIT ENTERO RD-L	Required
 Plasterboard	 MOUNTING KIT ENTERO RD-L	Required
 Stucanet	 MOUNTING KIT ENTERO RD-L	Required
 Wood	 MOUNTING KIT ENTERO RD-L	Required
 Concrete + plaster	 MOUNTING KIT ENTERO RD-L	Required
 Lintel + plaster	 MOUNTING KIT ENTERO RD-L	Required
 Hollow-core slab + plaster	 MOUNTING KIT ENTERO RD-L	Required
 Stretched ceiling	 MOUNTING KIT ENTERO RD-L CSC	Required
	 MOUNTING KIT ENTERO RD-L WSC	Required


ENTERO RD-L TRIMLESS 93010 W

28434 9310 W

FINISH YOUR SPECIFICATION


LED power supplies

#




300 90 63 LED POWER SUPPLY MULTI-POWER DIM9

1->6(6) / 1->5(5) / 1->5(4) / 1->5 (3)




300 90 68 LED POWER SUPPLY MULTI-POWER DIM5

1->4(3) / 1->4(2) / 1->3(2) / 1->3(1)




300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9

3->9(9) / 1->9(6) / 1->6(4)



300 90 110 LED POWER SUPPLY 350mA-DC / 10W DIM8

2->2




300 90 124 LED POWER SUPPLY MULTI-POWER DIM7

2->4(3) / 3(2) / 3(2) / 2(1) / 1(1)




300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5

2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)




21012 0010 LED POWER SUPPLY MULTI POWER

2->3 / 2->3 / 1->3



21012 0021 LED POWER SUPPLY MULTI POWER DIM1

2->4 / 2->4 / 1->4




21012 0035 LED POWER SUPPLY MULTI POWER DIM5

2->4 / 2->4 / 1->4


ENTERO RD-L TRIMLESS 93010 W

28434 9310 W




21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL

1->4 / 1->4 / 1->4 / 1->4 / 1->3




21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

2->2




21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

3->3




21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

2->2 / 2->2




21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

4->4 / 3->4




21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->3 / 1->3 / 1->3 / 1->2 / 1->1




21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->3



21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->3




21032 0315 LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5

1->3

ENTERO RD-L TRIMLESS 93010 W


28434 9310 W

Mounting kits



28400 0030 MOUNTING KIT ENTERO RD-L

Mounting kits stretched ceiling




28400 0090 MOUNTING KIT ENTERO RD-L CSC



28400 0150 MOUNTING KIT ENTERO RD-L WSC

Light altering devices



28500 0170 B ENTERO L HONEYCOMB SINGLE USE B

Notes: